

Time: 3 Hours**Marks: 80**

- N.B (1) Question No. 1 is compulsory
(2) Out of remaining questions attempt three
(3) Figures to right indicate full marks.

Q1 Solve any four

- a) Compare ground wave & sky wave propagation **(5)**
- b) Define modulation & explain any two need of modulation **(5)**
- c) State in brief different types of noise. **(5)**
- d) With reference to receiver define sensitivity, selectivity, fidelity and image frequency rejection **(5)**
- e) Draw BASK & BFSK signal for 10111010. **(5)**

- Q2** a) Explain with neat diagram Indirect method of FM generation **(10)**
b) Prove Friss formula with reference to noise factor in cascade. **(10)**

- Q3** a) What is multiplexing in communication system? Explain in brief transmitter and receiver of FDM. **(10)**
b) A sinusoidal carrier has an amplitude of 20 V & frequency of 200 KHz. It is amplitude modulated by a sinusoidal voltage of amplitude 6 V & frequency 1 KHz. Modulated voltage is developed across a 80 Ω resistance 1. Write the equation of modulated wave 2. Determine modulation index 3. Draw the spectrum of modulated wave & 4. Calculate total average power. **(10)**

- Q4** a) Explain generation & demodulation of PWM. **(8)**
b) In an AM receiver the loaded Q of antenna circuit at the input to mixer is 100. Calculate image frequency & its rejection at 1 MHz. **(8)**
c) State in brief different types of communication channel **(4)**

- Q5** a) Explain delta modulator transmitter & receiver with neat block diagram **(10)**
b) State & prove following properties of Fourier transform. **(10)**
(i) Time shifting (ii) convolution in time domain

- Q6** Write short notes (**Any Four**) **(20)**
1. Sampling theorem
 2. Frequency spectrum allocation
 3. Tropospheric scatter propagation
 4. Inter symbol interference
 5. Noise figure & noise factor